



## Wired Home WH-IR4000 Decora Style IR Target w/ Status Indicator

### FEATURES AND CHARACTERISTICS

1. Infrared frequency bandwidth: 38 kHz  $\pm$  2 kHz.
2. Compatible with almost all standard remote controls
3. Control range - 80 feet indoors, 15 to 20 feet in direct sunlight
4. System status indicator
4. Dimensions: 3/8" H x 2-3/4" W x 1-1/4" D

### INSTALLATION:

1. Run a length of shielded 3-conductor control cable (or Cat5 cable) from the Wired Home WH-IRH IR Hub to the WH-IR4000.
2. Remove 1/4" of insulation from both ends of all wires.
3. Loosen the set screws of the wire terminals on both the WH-IR4000 and the WH-IRH and insert the wires into the terminals accordingly. Tighten all screws to secure the wires. If using Cat 5 cable, use both conductors of a twisted pair for each connection. If status circuit is not used, use remaining pair for additional ground conductors to improve system performance on long runs.

**V+** 12 VDC power

**G-** Ground

**ST** Power status of the amplifier or receiver

**IR** IR Signal

4. Mount the IR target into a low voltage bracket. Install a Decora style cover.