

# 8CFX260Nd

**COAXIAL TRANSDUCER Preliminary Data Sheet** 

### **KEY FEATURES**

- High performance 8" coaxial speaker
- 2,5" / 2,85" voice coil diameter design (LF / HF)
- High power hadling 500 / 120 W program power
- High sensitivity 97 / 103 dB (1W / 1m) (LF / HF)
- Lightweight common neodymium magnetic circuit
- Cast frame speaker

- Features a waterproof carbon fiber cone
- Demodulation ring for linear and extended response and lower distortion
- For all high quality sound single point source applications including house of worship, studio monitors, home theater systems, movie theater, small PA systems, etc.



### TECHNICAL SPECIFICATIONS

Nominal diameter	200 mm		8 in
Rated impedance (LF/HF)			8/8Ω
Minimum impedance (LF/HF)		6	5,8 / 6,9 Ω
Power capacity 1 (LF/HF)		250 /	60 W <sub>AES</sub>
Program power <sup>2</sup> (LF/HF)		50	0 / 120 W
Sensitivity (LF/HF 3)	97 dB	1W /	1m @ Z <sub>N</sub>
	103 dB	1W /	1m @ Z <sub>N</sub>
Frequency range	100 - 20.000 Hz		
Recom. HF crossover	1,5 kHz or higher (12 dB/oct min slope)		
Voice coil diameter (LF/HF)	63,5 mm		2,5 in
	72,4 n	nm	2,85 in
BI factor			13,5 N/A
Moving mass			0,021 kg
Voice coil length			15 mm
Air gap height			7 mm
X <sub>damage</sub> (peak to peak)			20 mm

## THIELE-SMALL PARAMETERS4

Resonant frequency, f <sub>s</sub>	100 Hz
D.C. Voice coil resistance, R <sub>e</sub>	5,2 Ω
Mechanical Quality Factor, Q <sub>ms</sub>	4,8
Electrical Quality Factor, Q <sub>es</sub>	0,37
Total Quality Factor, Q <sub>ts</sub>	0,35
Equivalent Air Volume to C <sub>ms</sub> , V <sub>as</sub>	81
Mechanical Compliance, C <sub>ms</sub>	119 μm / N
Mechanical Resistance, R <sub>ms</sub>	2,7 kg / s
Efficiency, η <sub>0</sub>	2,2 %
Effective Surface Area, S <sub>d</sub>	0,022 m <sup>2</sup>
Maximum Displacement, X <sub>max</sub> <sup>5</sup>	6 mm
Displacement Volume, V <sub>d</sub>	132 cm <sup>3</sup>
Voice Coil Inductance, L <sub>e</sub>	0,23 mH

<sup>&</sup>lt;sup>1</sup> The power capaticty is determined according to AES2-1984 (r2003) standard.

<sup>&</sup>lt;sup>2</sup> Program power is defined as power capacity + 3 dB.

<sup>&</sup>lt;sup>3</sup> Sensitivity was measured at 1m distance, on axis, with 1W input, averaged in the range 1 - 7 kHz


<sup>4</sup> T-S parameters are measured after an exercise period using a preconditioning power test. The measurements are carried out with a velocity-current laser transducer and will reflect the long term parameters (once the loudspeaker has been working for a short period of time).

 $<sup>^{6}</sup>$  The  $X_{max}$  is calculated as  $(L_{vc} - H_{ag})/2 + (H_{ag}/3.5)$ , where  $L_{vc}$  is the voice coil length and  $H_{ag}$  is the air gap height.



# 8CFX260Nd

COAXIAL TRANSDUCER Preliminary Data Sheet



Note: Frequency response measured with loudspeaker standing on infinite baffle in anechoic chamber, 1W @ 1m

## **MOUNTING INFORMATION**

Overall diameter	212 mm	8,3 in
Bolt circle diameter	195 mm	7,7 in
Baffle cutout diameter:		
- Front mount	181 mm	7,1 in
Depth	134 mm	5,3 in
Net weight	4,9 kg	10,8 lb
Shipping weight	5,2 kg	11,5 lb

## **DIMENSION DRAWING**

